

## HOW TO FORWARD NUMBERS IN A TADIRAN SYSTEM

These commands can be typed from any menu in the CLI

**LIB 0 1** → Displays currently programmed libraries

**LIB 0 0** → Edits libraries

For this example, we will use LIB8005 to forward to the CCSi office

**Lib 0 0**

**FROM – 8005**

**TO – 8005**

LIB    8005

-----

NAME:

SHORT(5) - BLANK    You do not need to enter a short name

FULL(16) - John\_Cell            Any spaces need to be programmed as an underscore

TOLL\_OVERRIDE- Y        No change

NAME\_RETENTION\_OVERRIDE- Y        No Change

PROTECTED- N    No Change

USER\_CANNED\_MESSAGE# (0-15/N) -    NONE No Change

TNNT\_GRP - 0    No Change

PRIORITY\_PREEMPTION\_CALL- N        No Change

RSRVD\_TO\_BOSS\_GROUP(#/N) -        NONE    No Change

APPEND\_TO\_DIAL\_NUMBER\_AS\_SUFFIX (0:None,1:ANI\*DNIS\*,2:DNIS\*ANI\*): - 0        No Change

DIAL NUM = 12345678    Enter number as if you dialed it by hand

OUT TK =    9            Routing access number goes here. It is usually 9 but can be any number the client wishes

### **CCSi Communications**

365 Surryse Rd, Ste 220 | Lake Zurich, IL, 60047 | Tel: 630-241-0600 | Fax: 630-241-1071

Email: [tservices@ccscomm.com](mailto:tservices@ccscomm.com) | [www.ccscomm.com](http://www.ccscomm.com)

Once the Library has been programmed, you will need to point the DID to the Library

Type **TGDEF**

Enter **1** for Display

Look for the lines **DIAL IN/CALLER OUT OFFSET**

The number there (Usually 0 or 1) will indicate which OFFSET FILTER is used

In our example, the OFFSET FILTER in use will be 0

Type **ROOT 0 0 7 0 1** to display the OFFSET FILTER programming

Some carriers send 7 digits for filtering, other send 4

It may look like this

OFFSET FILTER# - 0

-----

FROM RECEIVED#   TO RECEIVED#   CORAL#

2345678      2345678      400

Or like this

OFFSET FILTER# - 0

-----

FROM RECEIVED#   TO RECEIVED#   CORAL#

5678      5678      400

### **DO NOT USE THE UPDATE OPTION IT DOES NOT WORK PROPERLY**

Select **3** to remove the DID you wish to point to another destination

When removed, Select **2** to add

The FROM RECEIVED# and TO RECEIVED# numbers need to match

The FROM DIAL# will be the **Library** that was just programmed

It should look like this

#### **CCSi Communications**

365 Surryse Rd, Ste 220 | Lake Zurich, IL, 60047 | Tel: 630-241-0600 | Fax: 630-241-1071

Email: [tservices@ccscomm.com](mailto:tservices@ccscomm.com) | [www.ccscomm.com](http://www.ccscomm.com)

FROM RECEIVED# - 3234545

TO RECEIVED# - 3234545

FROM DIAL# - 8005

OFFSET FILTER NUMBERS ADDED

Dial the DID number to verify that your programming is accurate. It should ring to the DIAL NUM = that was programmed in the Library.

Repeat as necessary

**CCSi Communications**

365 Surryse Rd, Ste 220 | Lake Zurich, IL, 60047 | Tel: 630-241-0600 | Fax: 630-241-1071

Email: [tservices@ccscomm.com](mailto:tservices@ccscomm.com) | [www.ccscomm.com](http://www.ccscomm.com)